

22418

12425

03 Hours / 70 Marks

Seat No.

--	--	--	--	--	--	--	--

-
- Instructions* – (1) All Questions are *Compulsory*.
- (2) Answer each next main Question on a new page.
- (3) Illustrate your answers with neat sketches wherever necessary.
- (4) Figures to the right indicate full marks.
- (5) Assume suitable data, if necessary.
- (6) Use of Non-programmable Electronic Pocket Calculator is permissible.
- (7) Mobile Phone, Pager and any other Electronic Communication devices are not permissible in Examination Hall.

Marks

- 1. Attempt any FIVE of the following :** **10**
- a) Define an electric motor.
 - b) State the function of field winding in DC motor.
 - c) Classify the different types of motors.
 - d) State the parts of the motors that are made of silicon steel stampings.
 - e) State the function of Breather in transformer.
 - f) State the reason why brushes in DC motor are made of carbon.
 - g) Write any two features of Auto transformer.

P.T.O.

2. Attempt any THREE of the following : 12

- a) Draw neat sketch of 3 points starter.
- b) State the material used for the following parts of DC motor -
 - i) Pole core
 - ii) Frame
 - iii) Commutator
 - iv) Field winding
- c) With neat sketch explain armature voltage control method of speed control used for DC shunt motor.
- d) Compare open circuit test and short circuit test of transformer.

3. Attempt any THREE of the following : 12

- a) Compare core type and shell type transformer on any four parameters.
- b) A 200 KVA 3000/250 V 50 Hz single phase transformer has 80 turns on its secondary winding.
Calculate –
 - i) Primary current
 - ii) Secondary current
 - iii) Maximum flux
 - iv) Primary turns.
- c) List out various losses in transformer. State how it can be reduced.
- d) State Flemings Left hand rule and Flemings Right hand rule.

4. Attempt any THREE of the following : 12

- a) State the advantages of three phase transformer over a bank of three single phase transformer.
- b) Give the criteria for selection of power transformer as per IS:10028 (Part I).
- c) State two applications and two features of isolation transformer.
- d) State any four features of welding transformer.
- e) Draw Equivalent circuit of transformer.

5. Attempt any TWO of the following : 12

- a) Compare single phase autotransformer and two winding transformer on following points.
 - i) No. of winding
 - ii) Efficiency
 - iii) Copper saving
 - iv) Cost
 - v) Electrical isolation
 - vi) Voltage Regulation
- b) State need for parallel operation of transformers. Also state two conditions for parallel operation and two advantages of parallel operation.
- c) 30 KVA, 2400/120 V, 50 Hz, 1ϕ transformer have $R_1 = 0.1\Omega$, $R_2 = 0.035\Omega$, $X_1 = 0.22\Omega$, $X_2 = 0.012\Omega$, Find the equivalent resistance, reactance and impedance referred to primary and secondary side.

6. Attempt any TWO of the following :**12**

- a) Find the all day efficiency of 500 KVA distribution transformer whose copper and iron losses at full load are 4.5 KW and 3 KW respectively. It is loaded as under per day.

No. of hours	6	6	6	6
Load in KW	450	300	200	0
P.f.	0.95	0.85	1	—

- b) State any six parts of three phase transformer. Also state the function of the part.
- c) Compare distribution transformer and power transformer.
-